

# grandMA2 full-size

Art.-No. 120111



The grandMA2 full-size represents MA Lighting's most powerful console and offers the control of conventional light, moving lights, LED fixtures and media from one platform.

Equipped with the most up-to-date technology and even some special features (e.g. keyboard drawer and multi-touch command screen), the grandMA2 is suitable for all lighting segments. It supplies an intuitive and fast control of all connected fixtures and channels. Furthermore the grandMA2 fader wing provides up to 60 extra motorized executor faders for an almost unlimited number of pages.

Moreover grandMA series 1-showfiles can be converted to be used with the grandMA2. And for yet easier operation, all command keys can be found in the same place on every console of the grandMA2 series. The grandMA2 offers extremely flexible and comfortable ways of programming, including nearly infinite numbers of presets, cues, pages, sequences and effects.

All grandMA2 consoles are optionally available as Silent Version with optimised fan for noise-sensitive environments.

## Features

- Real-time control for up to 65,536 parameters per session in connection with MA NPU (equivalent to 256 DMX universes)
- 8,192 HTP/LTP parameters
- 6 DMX outputs
- 3 internal TFT wide mode touchscreens (15.4" WXGA)
- 2 external TFT screens can be connected (UXGA, touchscreens accepted)
- 1 internal command screen – multi-touch (9" SVGA)
- 30 motorized executor faders
- Integrated keyboard drawer
- Built-in uninterruptible power supply (UPS)
- 2 etherCON connectors, 5 USB 2.0 connectors
- Motorized monitor wing
- 2 motorized A/B fader 100mm
- Individually backlit and dimmable silent (clickless) keys

## Scope of delivery

Art.-No.	Article	Quantity
120131	Dust cover grandMA2 full-size	1
120122	MA LED desk light grandMA2, angle plug 90° XLR 4pin, length 27"	2
4001091	MA Magnetic plate for easy labeling of 15 faders, (without pen)	2

built-in keyboard

## Technical Specifications

<b>Operating voltage/ Supply voltage</b>	120V/230V, 50/60Hz (automatic detection)
<b>Power</b>	350VA
<b>Dimensions</b>	1,284 x 204 x 661mm / 50.6 x 8 x 26inch
<b>Net weight</b>	46kg / 101lbs
<b>Output connectors</b>	6 x XLR 5pin (DMX) 2 x DVI (external monitor) 2 x etherCON 1 x MA Link (grandMA2 fader wing) 5 x USB 1 x DIN (MIDI) 2 x XLR 4pin (desklight)
<b>Input connectors</b>	1 x XLR 5pin (DMX) 1 x XLR 3pin (Sound) 1 x XLR 3pin (SMPTE) 1 x DIN (MIDI) 1 x Sub-D 25pol (Analogue Remote) 1 x powerCON

## Article

Art.-No.	Article
120111	grandMA2 full-size

## Accessories

Art.-No.		Article
121029		MA Case grandMA2 full-size, with wheels (by Amptown)
121030		MA Case grandMA2 full-size, without wheels (by Amptown)
120121	legacy	grandMA2 fader wing
130032	legacy	MA NPU (Network Processing Unit)
120123	legacy	MA Magnetic plate for easy labeling of 15 faders, (incl. Edding OHP pen)
129434		MA dust cover for two LED desk lights, 27"
120142	legacy	MA remote control package, incl. Apple iPad® (16GB)
120141	legacy	MA remote control package, incl. Apple iPod® touch (8GB)
120129		External keyboard USB for grandMA2, layout US
120127	legacy	External Laser mouse, USB, for grandMA2

## More product pictures

