

grandMA2 replay unit

Art.-No. 120115



The grandMA2 replay unit offers the same features and functions as the grandMA2 consoles in a 19" housing. It can be easily built into a rack and is therefore perfect for fixed installations like theatre, studio or architectural lighting control or as a backup solution.

The grandMA2 replay unit is a very safe playback/master controller, because there are no built-in faders or buttons to avoid faulty operations. Instead, the unit is operated by using the integrated touch screen or a mouse and keyboard, connected via USB. A wide range of interfaces assures the most flexible use and the best performance within architectural systems.

Features

- Real-time control for up to 65,536 parameters per session in connection with MA NPU (equivalent to 256 DMX universes)
- 4,096 HTP/LTP parameters
- 6 DMX outputs
- 2 external TFT screens can be connected (UXGA, touchscreens accepted)
- 1 internal command touchscreen (7")
- powerCON In and Out
- 2 etherCON connectors
- 3 USB2.0 connectors
- Various control interfaces

Scope of delivery

MA Quick Manual (4002123)

Technical Specifications

Operating voltage/ Supply voltage	120V/230V, 50/60Hz (automatic detection)
Power	150VA
Dimensions	485 x 445 x 126mm / 19 x 17.5 x 5inch
Net weight	11.3kg / 25lbs
Output connectors	6 x XLR 5pin (DMX) 2 x DVI (external monitor) 2 x etherCON 1 x MA Link (grandMA2 fader wing) 3 x USB 1 x DIN (MIDI)
Input connectors	1 x XLR 5pin (DMX) 1 x XLR 3pin (Sound) 1 x XLR 3pin (SMPTE) 1 x DIN (MIDI) 1 x Sub-D 25pol (Analogue Remote) 1 x powerCON

Article

Art.-No.	Article
120115	grandMA2 replay unit

Accessories

Art.-No.	Article
120121 legacy	grandMA2 fader wing
130032 legacy	MA NPU (Network Processing Unit)
120142 legacy	MA remote control package, incl. Apple iPad® (16GB)
120141 legacy	MA remote control package, incl. Apple iPod® touch (8GB)

More product pictures

