

grandMA2 light

SV (Silent Version)

Art.-No. 120162



The grandMA2 light has 4,096 parameters, 15 motorized executor faders and two touchscreens available. All further features and controls are identical to those on the grandMA2 full-size.

The grandMA2 light is the perfect tool to control all kinds of lighting genres like conventionals, moving lights, LEDs, video and media. It supplies an intuitive and fast control of all connected fixtures and channels. The grandMA2 light can handle an almost infinite number of presets, cues, pages, sequences and effects. It is ideally suited as a standalone console or as a backup device for the grandMA2 full-size. Moreover grandMA series 1-showfiles can be converted to be used with the grandMA2.

The Silent Version is equipped with an optimised fan and therefore ideally suited for noise-sensitive environments. It fulfills the international standards NC-25 (Noise Criterion, US) and NR-25 (Noise Rating, Europe).

Features

- Real-time control for up to 65,536 parameters per session in connection with MA NPU (equivalent to 256 DMX universes)
- 4,096 HTP/LTP parameters
- 6 DMX outputs
- 2 internal TFT wide mode touchscreens (15.4" WXGA)
- 2 external TFT screens can be connected (UXGA, touchscreens accepted)
- 1 internal command screen – multi-touch (9" SVGA)
- 15 motorized executor faders
- Integrated keyboard drawer
- Built-in uninterruptible power supply (UPS)
- 2 etherCON connectors, 5 USB 2.0 connectors
- Motorized monitor wing
- 2 motorized A/B fader (100mm)
- Individually backlit and dimmable silent (clickless) keys

Scope of delivery

Art.-No.	Article	Quantity
120132	Dust cover grandMA2 light and ultra-light	1
120122	MA LED desk light grandMA2, angle plug 90° XLR 4pin, length 27"	2
4001091	MA Magnetic plate for easy labeling of 15 faders, (without pen)	1

built-in keyboard

Technical Specifications

Operating voltage/ Supply voltage	120V/230V, 50/60Hz (automatic detection)
Power	350VA
Dimensions	935 x 204 x 652mm / 36.8 x 8 x 25.7inch
Net weight	37kg / 81.6lbs
Output connectors	6 x XLR 5pin (DMX) 2 x DVI (external monitor) 2 x etherCON 1 x MA Link (grandMA2 fader wing) 5 x USB 1 x DIN (MIDI) 2 x XLR 4pin (desklight)
Input connectors	1 x XLR 5pin (DMX) 1 x XLR 3pin (Sound) 1 x XLR 3pin (SMPTE) 1 x DIN (MIDI) 1 x Sub-D 25pol (Analogue Remote) 1 x powerCON

Article

Art.-No.	Article
120162	grandMA2 light, SV (Silent Version)

Accessories

Art.-No.		Article
121037		MA Case grandMA2 light and ultra-light, with wheels (by Amptown)
121038		MA Case for grandMA2 light and ultra-light, without wheels (by Amptown)
120121	legacy	grandMA2 fader wing
130032	legacy	MA NPU (Network Processing Unit)
120123	legacy	MA Magnetic plate for easy labeling of 15 faders, (incl. Edding OHP pen)
129434		MA dust cover for two LED desk lights, 27"
120142	legacy	MA remote control package, incl. Apple iPad® (16GB)
120141	legacy	MA remote control package, incl. Apple iPod® touch (8GB)
120129		External keyboard USB for grandMA2, layout US
120127	legacy	External Laser mouse, USB, for grandMA2

More product pictures

